

SANYO

SANYO Australia Pty Ltd

CONSUMER ELECTRONICS DIVISION

TECHNICAL BULLETIN No. 85 DATE: 15/12/10

SUBJECT: LCD22VT10DVD Low Volume High Pitch Noise

Fault:

The TV emits a low volume high pitch noise from the left speaker.

Cause:

Audio IC internal feedback fault.

Remedy:

Add 0.033uF (33nF) Polyester (Green cap) 63VAC 100VDC capacitor between SMD coil L4 and Ground as shown below.

Method:

Use double-sided sticky tape, or silicon glue to secure cap to the PCB.

