

Multi Zone/Region Free Conversions of DVD Players

DVD-5100/DVD-1500

Method:

The 2-firmware storage ICs have to be replaced.

Part Number:

Les has the ICs

Cost:

½-hour labour charges at the current rate. (\$44.00)

DVD-1500A

Method:

A firmware upgrade has to be applied from a CD-R disc according to Technical Bulletin TB 58 (Should come with the part). The customer can do it at his or her owns risk.

Part Number:

DVD1500AMULTIZONE

Cost:

Price of the upgrade CD-R (\$11.00 + \$5.50 P&H) Or, if the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

DVD-7201

Method:

A firmware upgrade has to be applied from a CD-R disc according to TB 59 (Should come with the part). The customer can do it, at his or her owns risk.

Part Number:

DVD7201MULTIZONE

Cost:

Price of the upgrade CD-R (\$11.00 + \$5.50 P&H) Or, if the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

DVD-SL20

Method:

A firmware upgrade has to be applied from a CD-R disc according to TB 57 (Should come with the part). The customer can do it, at his or her owns risk.

Part Number:

DVDSL20MULTIZONE

Cost:

Price of the upgrade CD-R (\$11.00 + \$5.50 P&H) Or, if the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

DC-AVD8501**Method:**

A firmware upgrade has to be applied from a CD-R disc according to TB 59 (Should come with the part). The customer can do it, at his or her owns risk.

Part Number:

DCAVD8501MULTIZONE

Cost:

Price of the upgrade CD-R (\$11.00 + \$5.50 P&H) Or, if the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

DC-TS750**Method:**

A firmware upgrade has to be applied from a CD-R disc according to TB (Should come with the part). The customer can do it, at his or her owns risk.

Part Number:

DCTS750MULTIZONE

Cost:

Price of the upgrade CD-R (\$11.00 + \$5.50 P&H) Or, if the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

DC-TS760**Method:**

A firmware upgrade has to be applied from a CD-R disc according to TB 56 (Should come with the part). The customer can do it, at his or her owns risk.

Part Number:

DCTS760R0MK

Cost:

Price of the upgrade CD-R (\$11.00 + \$5.50 P&H) Or, if the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

HVDX-300A/350**Method:**

1. Open the DVD tray.
2. Enter by the remote 0, 5, 2, 0, UP-ARROW, DOWN-ARROW, LEFT-ARROW, RIGHT-ARROW (Very bad English appears on screen, asking to put in the region code.)
3. Enter 0 to make it Region Free (or a Region number, if you want to set it to a specific Region)
4. Press the "Enter/OK" button. (The process now completes. You should power down and up the unit before playing a disc.)

Part Number:

N/A

Cost:

If the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

HVR-DX610/620/625

Method:

- 1.) Press the "Setup" button on the remote control.
- 2.) On the "Setup" Menu select "System Info" and press the [OK/ENTER] button.
- 3.) Enter 1101 with the remote control
- 4.) Press 0 for Multi Zone/Region Free (or the Region number, if you want to set it to a specific Region)

Part Number:

N/A

Cost:

If the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

DVD-DX500/510

Method:

- 1.) Open the disc tray
- 2.) Enter 8286 with the remote control
- 3.) Press 0 for Multi Zone/Region Free (or a Region number, if you want to set it to a specific Region)

Part Number:

N/A

Cost:

If the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

DVD-DX405/516

Method:

- 1.) Open the disc tray
- 2.) Enter 8286 with the remote control
- 3.) Press 0 for Multi Zone/Region Free (or a Region number, if you want to set it to a specific Region)

Part Number:

N/A

Cost:

If the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

DVR-DX600

Method:

- 1.) Press the "Setup" button on the remote control.
- 2.) On the "Setup" Menu select "Init Setup"
- 3.) On the "Init Setup" Menu select "System Info" and press the [OK/ENTER] button.
- 4.) Enter 1101 with the remote control
- 5.) Press 0 for Multi Zone/Region Free (or the Region number, if you want to set it to a specific Region)

Part Number:

N/A

Cost:

If the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

HVR-DX625HB

Method:

- 1.) Press the "Setup" button on the remote control.
- 2.) On the "Setup" Menu select "System Info" DO NOT press the [OK/ENTER] button.
- 3.) Enter 1101 with the remote control. A window will pop up showing current region.
- 4.) Press 0 for Multi Zone/Region Free (or the Region number, if you want to set it to a specific Region) then press the [OK/ENTER] button.

Part Number:

N/A

Cost:

If the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

HVR-DX700/710

Method:

- 1.) Press the "Setup" button on the remote control.
- 2.) On the "Setup" Menu select "Init Setup"
- 3.) On the "Init Setup" Menu select "System Info" and press the [OK/ENTER] button.
- 4.) Enter 1101 with the remote control
- 5.) Press 0 for Multi Zone/Region Free (or the Region number, if you want to set it to a specific Region)

Part Number:

N/A

Cost:

If the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).

DVD-DX517, DCHT818

Method:

- 1.) Open the disc tray.
- 2.) Enter 1369 with the remote control.
- 3.) Press 0 for Multi Zone/Region Free (or a Region number, if you want to set it to a specific Region).

Checking:

- 1.) Make sure no disc is inserted.
- 2.) Press the [SETUP] button.
- 3.) Enter 1379 with the remote control. The TV will show the current region code and firmware version.

Part Number:

N/A

Cost:

If the customer does not want to do it his or her self, ½-hour labour charge at the current rate (\$44.00).
